


## 3RD ANGLE PROJECTION DO NOT SCALE

Wiring List		
J1	J2	Signal Name
25 way D-Type	50 way IDC Header	-
1	1	OPTO_OUT_1+
14	2	OPTO_OUT_1-
2	3	OPTO_OUT_2+
15	4	OPTO_OUT_2-
3	5	OPTO_OUT_3+
16	6	OPTO_OUT_3-
4	7	OPTO_OUT_4+
17	8	OPTO_OUT_4-
5	9	OPTO_IN_1+
18	10	OPTO_IN_1-
6	11	OPTO_IN_2+
19	12	OPTO_IN_2-
7	17	+12V
20	18	+12V
8	19	GND
21	20	GND
9	21	422_OUT_1+
22	22	422_OUT_1-
10	23	422_OUT_2+
23	24	422_OUT_2-
11	25	422_OUT_3+
24	26	422_OUT_3-
12	27	422_OUT_4+
25	28	422_OUT_4-
13	29	GND

Unused Pins			
J2	13 - 16, 30 - 50		



All dimensions in millimetres (mm) and for reference only



© 2020 Active Silicon Limited

**Mechanical Overview** FireBird I/O Adapter

DRAWN Keith Baker 27-Jan-20 DRAWING NUMBER

SHT No. MO-AP20-0067-0101 2 of 2 3